

## SMA Bluetooth Connection

Your SMA solar inverter comes with built in Bluetooth which allows you to download the data from the unit.



- You can use an Android phone/tablet and communicate to the solar inverter via this 'Felix Solar app': [SEE HERE](#) (This will cost a small amount and is a third party app. This is not supported by Australia Wide Solar, simply an app we have seen customers have success with)
- STEPS
  1. Ensure your Android device is connected to your Wi-Fi network
  2. On the Android device open your Bluetooth setting and pair with the inverter – pass code "0000"
    - Check that you are pairing to your inverter (*not a neighbours SMA inverter – look at SN: xxxxxxxxx*)
  3. Open your new 'Felix Solar App'
    - Go to menu – then settings
      - Manage inverters
        - Add & Scan for devices
        - Select your inverter
        - Update fields to match your system
        - Save settings
      - Current inverter
        - Select your inverter
        - Select via a tick
          - ✓ Auto Bluetooth
          - ✓ Auto connect
          - ✓ Auto re-connect
    - Back to Felix Solar Main menu options
      - Connect to inverter
- Now your Android device will display the inverter yield

---

As a more advanced stage - You can upload data to this site: [www.pvoutput.org](http://www.pvoutput.org)

**This is has no Tech support available and can be difficult to set up.**

A sample pvoutput.org site is: [SEE HERE](#)

- If you have a computer on 24/7, you can use a USB Bluetooth Adapter to allow your Linux/Windows computer to communicate to pvoutput.org

